



## JA-188J Wireless panic button

The RC-188J is mainly used as a **wireless panic or emergency button**. It is designed to be a remote control for **setting/unsetting an alarm system** or remotely **controlling other appliances**.

o [Declaration of conformity - JA-188J \(PDF 312.77 kB\)](#)



### Description

It provides **tamper contacts** and **monitors the voltage** of its battery.

The system **reaction to button activation is optional**. The basic reaction is a panic alarm or setting/unsetting the system (selectable).

Other reactions can be chosen in control panel service mode.

### Technical specifications

**Voltage**

Lithium battery type CR14250 (1/2 AA) 3.6V/1.2 Ah  
Please note: Battery is not included

**Typical battery lifetime**

approximately 3 years (20 daily activations)

**Communication band**

868.1 MHz, Jablotron protocol

**Communication range**

approx. 300 metres (open area)

**Dimensions, weight**

80 x 80 x 29 mm, 60 g

**Operational environment according to**

EN 50131-1 class II. Indoor general

**Operational temperature range**

-10 °C to + 40 °C

**Complies with EN 50131-1, EN 50131-5-3, EN 50134-2**

grade 2

**Complies with**

ETSI EN 300220, EN 50130-4, EN 55022, EN 60950-1

**Can be operated according to**

ERC REC 70-03